

# Eclipse LED 32

## LED Keypad

### Description

LED 32 is a keypad with LED indication of zones, system troubles, alarm messages and arming type. It is a part of the ECLIPSE series alarm systems.

The keyboard provides 1 input zone and 1 PGM output. LED 32 is suitable for programming and management of systems up to 8 independent areas and up to 32 zones.

### Technical Specifications

Power Supply from the control panel . . .	9-18V (nom. 14V)
Consumption . . . . .	Min. 60mA / Max. 140mA
Area Indication . . . . .	8
Zone Indication . . . . .	32
Panic buttons . . . . .	Yes
Proxi Reader . . . . .	Yes (option)
Voice Guide . . . . .	Yes (option)
Buttons . . . . .	Rubber
Operation temperature . . . . .	-20 ÷ +50°C
Tamper . . . . .	Yes
Dimensions . . . . .	108x134x23mm



### Functional Specifications

- Shortcut buttons to additional menus – Memory, Troubles display and Bypassed zones;
- Quick buttons for all arming modes;
- 3 fast button combinations for sending of PANIC, MEDICAL and FIRE alarm messages to a central monitoring station;
- The system parameters can be fully programmed;
- Supports 2 programming types: 4-digit addresses and 3-digit operations;
- Adjustable intensity of backlight for the display and buttons;
- Adjustable buzzer volume;
- Bi-directional TAMPER switch.

### Packing Information

- **Master box** - 50 units LED 32, dimensions 496 x 305 x 206 mm

### Compatible Product Range

- **Eclipse 8** - Alarm Control Panel
- **Eclipse 32** - Alarm Control Panel

### Contact Information