



BRAVO MOUT

Communication Module with outputs

Description

BRAVO MOUT is a communication module with outputs and is designed for operation in BRAVO wireless intruder alarm systems.

The module is mounted into BRAVO panel via serial interface connection. The BRAVO MOUT module sends messages for events to radio transmitter connected to its outputs.

Other application of BRAVO MOUT module is for connecting of wired outdoor siren to the BRAVO system configuration.

The module can be used also for realizing of home automation projects through the PGM outputs.

The module can be programmed via ProsTE software or AjaxWEB user web interface.



Technical and Functional Specifications

- Built-in mounting in BRAVO panel;
- Serial interface connection on slot;
- Connection of radio transmitter for sending messages for events to monitoring station: Arm/Disarm, Burglary alarm, Tamper/Lost device, Panic alarm, Fire and Siren;
- Connection of wired outdoor siren (powered on with external power supply 12V DC);
- 6 not programmable PGM outputs, OC, up to 100mA, active state 0 (GND), normal state 1;
- Remote management of the outputs (MobileTTE*);
- LED indication for module state;
- Direct programming via ProsTE software;
- Remote programming via AjaxWEB** software.

* MobileTTE is free mobile application for iOS or Android devices.

** AjaxWEB is part of Ajax Server installation.

Packing Information

- **Single packing box** - 1 unit BRAVO MOUT, dimensions 107 x 31 x 76mm

Compatible Product Range

- **BRAVO EXT** - Wireless panel with external power supply
- **BRAVO INTR** - Wireless panel with built-in power supply
- **TP2000** - Radio transmitter
- **SR200** - Wired outdoor siren
- **SR300** - Wired outdoor siren
- **SR400** - Wired outdoor siren

Contact Information