

Eclipse 32

Alarm Control Panel

Description

Eclipse 32 is up to 32 zone control panel appropriate for security of homes, medium sized commercial premises and offices. The panel supports 8 independent areas (partitions) with individual programming.

Eclipse 32 has 8 physical inputs for connecting of detectors; the zone balancing is with 1 or 2 balancing resistors or doubling zone connection. In the hardware system configuration the installer can choose among 9 connection styles in the zones. The full configuration of 32 zone can be realized with doubling zone connection (16 logical zones on the control PCB) and 1 Zone expander for 8 zones (16 logical zones) or without zone doubling with 3 zone expanders.

Technical Specifications

Mains Supply Voltage. 230V \pm 10%
 Mains Transformer 15 - 26 VAC / 50 VA
 Back-up Battery 12V / 7 Ah
 Battery Charger 13.8 V / 0,8A Resettable fuse
 Current consumption 2,5A (from external devices)
 Power output 13.8 V DC / 0,5A Resettable fuse
 Operating Temperature. -10°C / +50°C
 Dimensions, plastic box 335 x 290 x 105 mm



Functional Specifications

Zones. 8 on board; expandable to 32
 Balancing of zones 1 or 2 balancing resistors; doubling zone connection
 Areas 8
 Outputs 4 low current (up to 100mA) + 1 powerful (up to 1A)
 Access Codes 4/6 digit; 64 user, 4 maintenance, 1 engineer
 Memory LOG. 1024 events with date and time
 Digital Communicator. 4 telephone numbers; built in; CIA and Contact ID
 Programming 3 types - by addresses, by operations, tree structure
 Access Control via proximity readers; time slots
 Connection styles 9 types

Packing Information

• **Master box, plastic box** - 5 units Eclipse 32, dimensions 560 x 362 x 320 mm

Compatible Product Range

- **LED 32** - keypad
- **LCD 32** - keypad
- **LCD 32S** - keypad
- **LED 16** - keypad
- **Zone 8** - zone expander
- **PGM 8** - PGM expander
- **TITAN series** - PIR detectors
- **SR 105; SR110** - indoor sirens
- **SR 200; SR300** - outdoor sirens
- **SensoMAG INTR** - fire detectors with relay base 12V
- **GBD10, GBD20** - glass break detectors
- **ARGUS** - Universal GSM communication module
- **AJAX GSM/GPRS** - Universal GSM/GPRS communication module
- **AJAX SP** - WEB application for monitoring and control
- **ProSTE** - Specialized programming software
- **MDU 2; MDU V** - remote control modules

Contact Information