

# Eclipse LED 8

## LED Keypad

### Description

LED 8 is a keypad with LED indication of zones, troubles and alarm events. It is part of the ECLIPSE 8 alarm system.

The keyboard provides 1 input zone. LED 8 is suitable for programming and management of systems up to 8 zones organized in common protected area.

### Technical Specifications

Power Supply from the control panel . . .	9-18V (nom. 14V)
Consumption . . . . .	Min. 50mA / Max. 80
Area Indication . . . . .	1
Zone Indication. . . . .	8
Panic buttons . . . . .	Yes
Buttons . . . . .	Rubber
Operation temperature . . . . .	-20 ÷ +50°C
Tamper . . . . .	Yes
Dimensions . . . . .	100x90x24mm



### Functional Specifications

- Quick buttons for all arming modes;
- 3 fast button combinations for sending of PANIC, MEDICAL and FIRE alarm messages to a central monitoring station;
- The system parameters can be fully programmed;
- Supports 2 programming types: 4-digit addresses and 3-digit operations;
- Adjustable intensity of back light for the buttons;
- Adjustable buzzer volume;
- Bi-directional TAMPER switch.

### Packing Information

- **Master box** - 80 units LED 8, dimensions 496 x 305 x 206 mm

### Compatible Product Range

- **Eclipse 8** - Alarm Control Panel

### Contact Information