



BRAVO PIR EXT GJD

Wireless Outdoor Detector

Description

BRAVO PIR EXT GJD is a wireless outdoor motion detector. It can be used with BRAVO wireless intruder system or with ECLIPSE systems through the wireless expander module. The detector is battery powered and can be located in a distance up to 400m away from the control panel. BRAVO PIR EXT GJD covers the standard EN50131, GRADE 2.

Technical Specifications

| | |
|-----------------------------|---------------------------|
| Detection range | programmable from 10-30 m |
| Battery | 3x3V/1500mAh, CR123A type |
| Battery life | 3 years |
| Operation frequency | 868MHz |
| Radio distance (open space) | up to 400m |
| Operation temperature | -20°C ÷ +55°C |
| White Light Immunity | 50 000 Lux |
| Walk detection speed | 0.3 m/s ÷ 3.0 m/s |
| Coverage | 10-70° detection angle |
| Adjustment | 180° pan, 90° tilt |
| Mounting height | up to 3 m |
| Number of detection zones | 28 |
| Dimensions | 145 x 120 x 155mm |
| Current | 35 µA |
| Degree of protection | IP 65 |

GJD
DETECT & SECURE



Functional Specifications

- Quick and easy mounting in the protected site
- Tamper switch for self-protection of the box and back tamper
- Reset button for restoring the factory settings

Packing Information

- **Single packing box** - 1 unit BRAVO PIR EXT GJD, dimensions 146x138x116 mm
- **Weight** - 0.318 kg

Compatible Product Range

- **BRAVO EXT** - Wireless panel with external power supply
- **BRAVO INTR** - Wireless panel with built-in power supply
- **ECLIPSE WL** - Wireless expander module for ECLIPSE control panels

Contact Information