



Luxriot USB PTZ joystick



Features:

- Full Luxriot Integration
- Server and client side control
- 10 programmable preset buttons
- Joystick Zoom, twist left or right
- Supports up to 128 presets in Luxriot software
- Control IP and Analog PTZ cameras
- Easy to use and install
- ROHS Compliant Specification:

Option 5 Joystick travel	36° (18° from center)
Centering	single spring, omnidirectional
Housing	high impact, glass-filled nylon
Breakout force	.109Nm
Operation force	.151Nm
Maximum force	.169Nm
Operating temperature	-40°C to +85°C
Life cycles	10,000,000
Supply voltage (USB bus):	Vdd = 5V ± .5V
Supply current (USB bus)	32mA
Width	6.15" (15.6cm)
Length	6.65" (16.9cm)
Height	4.97" (12.6cm)